





T.			$U_f$	$I_f$	$U_a$	$U_g$	$I_a$	$S$	$\mu$	$R_i$	$R_o$	$P_a$	
			V	A	V	V	mA	mA/V	V/V	k $\Omega$	k $\Omega$	W	
DC 93	eur	1	1,4/2,8	0,2/0,1	$\begin{cases} 100 \\ 150 \end{cases}$	-5	10	2,4	8,3	3,5		1,8	
									maximum				
DD 960	RFT	1	1,4/2,8	0,2/0,1	$\begin{cases} 67,5 \\ 100 \\ 150 \end{cases}$	-3	9	2,45	8,3	3,4	4,5	1,8	
							-6,5	10	2,5	8,3	3,3		5
									maximum				
2 II 1 II <sup>1)</sup>	CCCP	2	1,2/2,4	0,12/0,06	90	-4,5	11,6	2,5	7,5	3			

<sup>1)</sup> vide gr. 198



DC93



2П1П