




T.			U_f V	I_f A	Cl.	f MHz	U_a V	U_{g2} V	U_{g3} V	U_{g1} V	S mA/V	μ (g_2/g_1)	I_k mA	P_a W
$\Gamma\text{Ж}2$	СССР	1	10/20	1/0,5	stat	20	750	250	40	-60	4,7	15	120	40
$K\text{Ж}1$	СССР	1	10/20	0,6/0,3	stat	50	400	250	30	¹⁾	5,5		120	20

¹⁾ $R_{g1} = 60 \text{ k}\Omega$

T.	C_{g1}	C_a	$C_{g1/a}$
	pF	pF	pF
$\Gamma\text{Ж}2$	12	11	0,22
$K\text{Ж}1$	9,5	7,5	0,3



Equivalents

$\Gamma\text{-}411$	СССР = $K\text{Ж}1$
$\Gamma\text{-}413$	СССР = $\Gamma\text{Ж}2$